



Level 3 Technical Level

Design Engineering

Mechatronic Engineering

F/506/5952

Unit 1 Materials technology and science

Mark scheme

January 2018

Version: 1.0 Final



1 8 1 A F / 5 0 6 / 5 9 5 2 / M S

Mark schemes are prepared by the Lead Assessment Writer and considered, together with the relevant questions, by a panel of subject teachers. This mark scheme includes any amendments made at the standardisation events which all associates participate in and is the scheme which was used by them in this examination. The standardisation process ensures that the mark scheme covers the students' responses to questions and that every associate understands and applies it in the same correct way. As preparation for standardisation each associate analyses a number of students' scripts: alternative answers not already covered by the mark scheme are discussed and legislated for. If, after the standardisation process, associates encounter unusual answers which have not been raised they are required to refer these to the Lead Assessment Writer.

It must be stressed that a mark scheme is a working document, in many cases further developed and expanded on the basis of students' reactions to a particular paper. Assumptions about future mark schemes on the basis of one year's document should be avoided; whilst the guiding principles of assessment remain constant, details will change, depending on the content of a particular examination paper.

Further copies of this Mark Scheme are available from aqa.org.uk

| Question | Marking Guidance | Marks |
|----------|------------------|-------|
| 01 | B | 1 |
| 02 | D | 1 |
| 03 | C | 1 |
| 04 | A | 1 |
| 05 | A | 1 |
| 06 | D | 1 |
| 07 | C | 1 |
| 08 | B | 1 |
| 09 | A | 1 |
| 10 | B | 1 |

| Question | Marking Guidance | Marks | | | | | | | | | | | | | | | |
|--------------------------|--|--|-------|---|-----------------------|-----------------------|--|-------------------------|-----------------|---|--------------------------|---|--|----------|--|--|---|
| 11.1 | <p>Complete Table 1 by entering the material class and a suitable application. The top row has been completed for you as an example.</p> <p>1 mark for each correct answer up to a maximum of 6 marks. Max 3 marks for class and max 3 marks for typical use.</p> <table border="1" data-bbox="311 608 1330 1477"> <thead> <tr> <th data-bbox="311 608 568 691">Material</th><th data-bbox="568 608 859 691">Class</th><th data-bbox="859 608 1330 691">Typical use (any other suitable responses)</th></tr> </thead> <tbody> <tr> <td data-bbox="311 691 568 826">Melamine formaldehyde</td><td data-bbox="568 691 859 826">Thermosetting polymer</td><td data-bbox="859 691 1330 826">Household items – such as glasses, cups, bowls and plates. Toilet seats, light switches and pan handles.</td></tr> <tr> <td data-bbox="311 826 568 932">Thermochromic materials</td><td data-bbox="568 826 859 932">Smart Materials</td><td data-bbox="859 826 1330 932">Sunglasses, data storage, solar energy storage. Temperature indicators.</td></tr> <tr> <td data-bbox="311 932 568 1102">Polyvinyl chloride (PVC)</td><td data-bbox="568 932 859 1102">Thermoplastic polymers Don't allow polymers.</td><td data-bbox="859 932 1330 1102">Construction profiles, medical devices, roofing membranes, credit cards, children's toys and casing for wires. Allow glue and bottles.</td></tr> <tr> <td data-bbox="311 1102 568 1477">Titanium</td><td data-bbox="568 1102 859 1477">Non-ferrous metals. Don't allow metal on its own.</td><td data-bbox="859 1102 1330 1477">Used as a pigment in house paint, artists' paint, plastics, enamels and paper, sunscreens, power plant condensers, protection of hulls of ships, submarines and other structures exposed to seawater. Surgical applications such as in joint replacements (especially hip joints) and tooth implants. Exhaust systems.</td></tr> </tbody> </table> <p>Or other suitable responses.</p> | Material | Class | Typical use (any other suitable responses) | Melamine formaldehyde | Thermosetting polymer | Household items – such as glasses, cups, bowls and plates. Toilet seats, light switches and pan handles. | Thermochromic materials | Smart Materials | Sunglasses, data storage, solar energy storage. Temperature indicators. | Polyvinyl chloride (PVC) | Thermoplastic polymers Don't allow polymers. | Construction profiles, medical devices, roofing membranes, credit cards, children's toys and casing for wires. Allow glue and bottles. | Titanium | Non-ferrous metals. Don't allow metal on its own. | Used as a pigment in house paint, artists' paint, plastics, enamels and paper, sunscreens, power plant condensers, protection of hulls of ships, submarines and other structures exposed to seawater. Surgical applications such as in joint replacements (especially hip joints) and tooth implants. Exhaust systems. | 6 |
| Material | Class | Typical use (any other suitable responses) | | | | | | | | | | | | | | | |
| Melamine formaldehyde | Thermosetting polymer | Household items – such as glasses, cups, bowls and plates. Toilet seats, light switches and pan handles. | | | | | | | | | | | | | | | |
| Thermochromic materials | Smart Materials | Sunglasses, data storage, solar energy storage. Temperature indicators. | | | | | | | | | | | | | | | |
| Polyvinyl chloride (PVC) | Thermoplastic polymers Don't allow polymers. | Construction profiles, medical devices, roofing membranes, credit cards, children's toys and casing for wires. Allow glue and bottles. | | | | | | | | | | | | | | | |
| Titanium | Non-ferrous metals. Don't allow metal on its own. | Used as a pigment in house paint, artists' paint, plastics, enamels and paper, sunscreens, power plant condensers, protection of hulls of ships, submarines and other structures exposed to seawater. Surgical applications such as in joint replacements (especially hip joints) and tooth implants. Exhaust systems. | | | | | | | | | | | | | | | |
| 11.2 | <p>The frame of the mountain bike is commonly manufactured from which material?</p> <p>Aluminium alloy or Carbon Fibre Reinforced Plastic (CFRP) or low carbon steel. Don't allow high carbon steel or stainless steel.</p> <p>1 mark for aluminium. 1 mark for carbon fibre. 1 mark carbon. 1 mark for alloy. 1 mark for reinforced plastic. 1 mark steel.</p> <p>up to a maximum of 2 marks</p> | 2 | | | | | | | | | | | | | | | |

| Question | Marking Guidance | Marks |
|----------|---|-------|
| 11.3 | <p>Give two reasons why this material is used.</p> <p>Both classes have good strength. Both classes of material are low density. Both classes of material are stiff. Both classes of material can be used in manufacturing quite easily.</p> <p>Don't allow malleable.</p> <p>1 mark each for any of the above or other suitable reason up to a maximum of 2 marks.</p> | 2 |
| 12.1 | <p>Name the three labelled regions indicated on Figure 2.</p> <p>A Point: The eutectic point. Allow melting point as a BoD. B Phase: The liquid phase. C Phase: The solid phase.</p> <p>1 mark for each correct point made.</p> | 3 |
| 12.2 | <p>Describe the stages of the process for case hardening of steel.</p> <p>Carbon is added to the outer surface of the steel, to a depth of approximately 0.03mm. The steel is heated to red heat. It may only be necessary to harden one part of the steel and so heat can be concentrated in this area. The steel is removed from the brazing hearth with blacksmiths' tongs and plunged into case hardening compound and allowed to cool a little. The case hardening compound is high in carbon. The steel is heated again to a red colour, removed from the brazing hearth and plunged into cold, clean water. The steel rod should now have a hardened outer surface and a flexible, soft interior. The process can be repeated to increase the depth of the hardened surface.</p> <p>1 mark for carbon is added to the outer surface of the steel. 1 mark for 0.03 mm (or similar depth, don't be too harsh). 1 mark Steel is heated to red heat. 1 mark for case hardening compound. 1 mark for heating steel to red heat. 1 mark for cold water. 1 mark for repeating process to get extra depth.</p> <p>or other suitable responses up to a maximum of 7 marks.</p> | 7 |

| Question | Marking Guidance | Marks |
|----------|--|-------|
| 13.1 | <p>Describe how a diode works in an electronic circuit.</p> <p>A diode is a discrete component that allows current to flow in one direction only. It is a polarised component with two leads, called the cathode and the anode. The cathode is normally marked with a silver or coloured band or the symbol '-'. If the anode is connected to a higher voltage than the cathode, current will flow from anode to cathode. This is called forward bias. If the diode is put in the circuit back to front, so that the voltage at the cathode is higher than the voltage at the anode, the diode will not conduct electricity. This is called reverse bias.</p> <p>1 mark for allows current to flow in one direction only. 1 mark for anode. 1 mark for cathode. 1 mark for forward bias. 1 mark for reverse bias.</p> <p>or other suitable responses up to a maximum of 5 marks.</p> | 5 |
| 13.2 | <p>Describe how electromagnetic induction is used in a voltage transformer.</p> <p>When a DC current pass through a long straight conductor a magnetising force, H (field strength) and a static magnetic field, B (flux density) is developed around the wire. If the wire is then wound into a coil, the magnetic field is greatly intensified producing a static magnetic field around itself forming the shape of a bar magnet giving a distinct North and South pole. The magnetic flux developed around the coil being proportional to the amount of current flowing in the coils windings. If additional layers of wire are wound upon the same coil with the same current flowing through them, the static magnetic field strength would be increased.</p> <p>1 mark for magnetising force. 1 mark for magnetic field. 1 mark for coil of wire intensifying the magnetic field. 1 mark for magnetic flux developed around the coil being proportional to the amount of current flowing in the coils windings. 1 mark for additional layers of wire increasing magnetic field strength.</p> <p>or other suitable responses up to a maximum of 5 marks.</p> | 5 |

| Question | Marking Guidance | Marks |
|----------|--|-------|
| 14.1 | <p>Describe what is meant by latent heat of fusion.</p> <p>1 mark for a limited response, such as the energy required to melt a solid</p> <p>2 marks for a detailed response, such as the heat absorbed by a unit mass of a given solid at its melting point that completely converts the solid to a liquid at the same temperature</p> | 2 |
| 14.2 | <p>Describe in detail the operation of a heat pump using a suitable example.</p> <p>Award up to 6 marks as follows:</p> <p>Heat pumps transfer heat from an area of relatively high temperature to an area or relatively low temperature, or vice versa (1 mark). They do this by circulating a substance called a refrigerant (1 mark) through a cycle of evaporation and condensation (1 mark). A compressor pumps the refrigerant between two heat exchanger coils (1 mark). In one coil, the refrigerant is evaporated at low pressure and absorbs heat from its surroundings (1 mark). The refrigerant is then compressed en route to the other coil, where it condenses at high pressure (1 mark). At this point, it releases the heat it absorbed earlier in the cycle (1 mark).</p> <p>An example of a heat pump: Air conditioning, fridge, freezer, HVAC systems. Don't allow radiator as an example.</p> <p>1 mark for any of these or any other suitable response.</p> | 6 |
| 14.3 | <p>What is the SI unit of thermal energy?</p> <p>1 mark for the Joule or Nm or J.</p> | 1 |
| 14.4 | <p>What is the SI unit of thermal power?</p> <p>1 mark for the Watt or Nm / s allow J / s.</p> | 1 |

| Question | Marking Guidance | Marks |
|----------|--|-------|
| 15.1 | <p>Calculate the length of the beam, L_t, at 70°C and -30°C if $\alpha = 16.0 \times 10^{-6} \text{m m}^{-1} \text{K}^{-1}$</p> <p>$L_t = L_0(1 + \alpha\Delta T)$ inserting values, we have:</p> $L_t = 6(1 + 16.0 \times 10^{-6}(70^{\circ} - 20^{\circ}))$ $L_t = 6.005 \text{ m to 3 d.p. At } 70^{\circ}\text{C.}$ $L_t = 6(1 + 16.0 \times 10^{-6}(-30^{\circ} - 20^{\circ}))$ $L_t = 5.995 \text{ m to 3 d.p. At } -30^{\circ}\text{C.}$ <p>1 mark for use of the correct values. 1 mark for the correct way to calculate ΔT. 1 mark for the correct answer. 1 mark for the use of 3 d. p. At 70°C. 1 mark for the correct way to calculate ΔT. 1 mark for the correct answer. 1 mark for the use of 3 d. p. At -30°C.</p> | 7 |
| 15.2 | <p>State two mechanical properties and one physical property required for a steel beam.</p> <ul style="list-style-type: none">• Tensile strength.• Compressive strength.• Elasticity.• Toughness.• Hardness.• Corrosion resistance.• Low thermal expansion.• Torsional strength / stiffness.• High melting point.• Stiffness. <p>1 mark for any of the above or other suitable response up to a maximum of 3 marks. Don't be too harsh, especially if a candidate names three mechanical properties.</p> | 3 |

| Question | Marking Guidance | Marks |
|----------|--|-------|
| 16 | <p>If Gear A is rotating at 30 RPM in a clockwise direction, determine the speed and direction of Gear D using the information from Table 2.</p> $R = \frac{\omega_{in}}{\omega_{out}} = \frac{N_{out}}{N_{in}}$ <p>A rotates clockwise at 30RPM.</p> $\frac{\omega_{in}}{\omega_{out}} = \frac{N_{out}}{N_{in}} \therefore \frac{\omega_A}{\omega_B} = \frac{N_B}{N_A} \text{ and } \omega_B = \frac{\omega_A N_A}{N_B}$ <p>Thus: $\omega_B = \frac{30 \times 120}{40} = 90 \text{ RPM Anticlockwise.}$</p> <p>Because gear C is connected to gear B they will be rotating at the same speed in the same direction.</p> $\frac{\omega_C}{\omega_D} = \frac{N_D}{N_C} \text{ and } \omega_D = \frac{\omega_C N_C}{N_D}$ <p>Thus: $\omega_D = \frac{90 \times 80}{20} = 360 \text{ RPM Clockwise.}$</p> <p>1 mark for the correct formula. 1 mark for the correct symbols. 1 mark for the correct transposition. 1 mark for the correct values. 1 mark for the correct answer. 1 mark for correctly stating $\omega_B = \omega_C$. 1 mark for the correct transposition. 1 mark for the values. 1 mark for the correct answer.</p> | 10 |

| Question | Marking Guidance | Marks |
|----------|------------------|-------|
|----------|------------------|-------|

| | | |
|------|--|---|
| 17.1 | <p>Describe the effects of cold working an aluminium alloy.</p> <p>Cold working produces additional dislocations within the metal structure. When two or more dislocations meet, the movement of one tends to interfere with the movement of the other. The more dislocations there are, the more they will hinder each other's movement.</p> <p>As the working continues, however, the movement of the dislocations becomes more difficult. This increases the strength of the metal and also makes it stiffer.</p> <p>1 mark for dislocations. 1 mark for movement of one tends to interfere with the other. 1 mark for movement of the dislocations becomes more difficult. 1 mark for increases strength (accept stiffness or hardness) of the materials. 1 mark for increase in internal stress.</p> <p>Maximum of 4 marks.</p> | 4 |
|------|--|---|

| Question | Marking Guidance | Marks |
|----------|------------------|-------|
|----------|------------------|-------|

| | | |
|------|---|---|
| 17.2 | <p>Explain in detail how normalising changes the properties of steel.</p> <p>Award up to 6 marks as follows:</p> <p>Normalising involves heating the steel to just above its upper critical point (1 mark), soaking it for a short period at that temperature (1 mark) and then allowing it to cool in air (1 mark). This creates a fine grain structure (1 mark) which results in a tougher (1 mark), more ductile (1 mark) material. It also eliminates columnar grains and dendritic segregation (1 mark) that sometimes occurs during casting (1 mark). It improves machinability (1 mark) and improved dimensional stability if the material is subjected to further heat treatment processes (1 mark).</p> <p>Any other relevant point.</p> | 6 |
|------|---|---|

Assessment outcomes coverage

| Assessment Outcomes | Marks and % of marks available in section A | Marks and % of marks available in section B | Total Marks |
|---------------------|---|---|-------------|
| AO1: | 10 marks 20% | 10 marks 33.3% | 20 |
| AO2: | 10 Marks 20% | 00 marks 00% | 10 |
| AO3: | 10 Marks 20% | 10 marks 33.3% | 20 |
| AO4: | 10 Marks 20% | 00 marks 00% | 10 |
| AO5: | 10 Marks 20% | 10 marks 33.3% | 20 |
| Total Marks | 50 | 30 | 80 |

| Question | Assessment Outcome 1 | Assessment Outcome 2 | Assessment Outcome 3 | Assessment Outcome 4 | Assessment Outcome 5 |
|---------------|----------------------|----------------------|----------------------|----------------------|----------------------|
| 1 | 1 | | | | |
| 2 | 1 | | | | |
| 3 | 1 | | | | |
| 4 | 1 | | | | |
| 5 | 1 | | | | |
| 6 | 1 | | | | |
| 7 | 1 | | | | |
| 8 | 1 | | | | |
| 9 | 1 | | | | |
| 10 | 1 | | | | |
| 11 | | 10 | | | |
| 12 | | | 10 | | |
| 13 | | | | 10 | |
| 14 | | | | | 10 |
| 15 | 10 | | | | |
| 16 | | | | | 10 |
| 17 | | | 10 | | |
| Totals | 20 | 10 | 20 | 10 | 20 |