OCR
Oxford Cambridge and RSA

Cambridge Technicals

Engineering

Unit **2:** Science for engineering

Level 3 Cambridge Technical Certificate/Diploma in Engineering
05822 - 05825

Mark Scheme for January 2017

Oxford Cambridge and RSA Examinations

OCR (Oxford Cambridge and RSA) is a leading UK awarding body, providing a wide range of qualifications to meet the needs of candidates of all ages and abilities. OCR qualifications include AS/A Levels, Diplomas, GCSEs, Cambridge Nationals, Cambridge Technicals, Functional Skills, Key Skills, Entry Level qualifications, NVQs and vocational qualifications in areas such as IT, business, languages, teaching/training, administration and secretarial skills.

It is also responsible for developing new specifications to meet national requirements and the needs of students and teachers. OCR is a not-for-profit organisation; any surplus made is invested back into the establishment to help towards the development of qualifications and support, which keep pace with the changing needs of today's society.

This mark scheme is published as an aid to teachers and students, to indicate the requirements of the examination. It shows the basis on which marks were awarded by examiners. It does not indicate the details of the discussions which took place at an examiners' meeting before marking commenced.

All examiners are instructed that alternative correct answers and unexpected approaches in candidates' scripts must be given marks that fairly reflect the relevant knowledge and skills demonstrated.

Mark schemes should be read in conjunction with the published question papers and the report on the examination.

OCR will not enter into any discussion or correspondence in connection with this mark scheme.

© OCR 2017

Question			Solution	Marks	Guidance
1	**(a)**				One mark for each correct line of the table.
				1	
			μ (micro) — 10^{-6}	1	Accept powers alone i.e. -6, 6,3, -3.
			M (mega) — 10^{6}	1	
			k (kilo) — 10^{3}	1	
			m (milli) — 10^{-3}	1	
1	**(b)**		Relative error: Ratio of absolute error and true value (given in percentages), OR absolute error divided by true value.	1	Accept absolute error over true value.
1	**(c)**	**(i)**	($X =$)0.00236;	1	
			Relative error $= \Delta X/X = (0.002362 - 0.00236)/0.002362$	1	Evidence of correct calculation
			Relative error $= 0.00085$ $(= 0.085\%)$	1	Ignore sign (subtraction can be done either way round)
		(ii)	($X =$)0.002;	1	
			Relative error $= \Delta X/X = (0.002362 - 0.002)/0.002362 = 0.153$ $(= \pm15.3\%)$	1	Ignore sign as above (2nd mark of (i) could be awarded here if not awarded in (i)
			QUESTION TOTAL	**10**	

	Question		Solution	Marks	Guidance
2	**(a)**	**(i)**	$F_g = mg = 20 \times 9.8 = 196 \underline{N}$	1	Unit is required. ACCEPT 200 N for 2 sf.
2	**(a)**	**(ii)**	(Using Pythagoras) $F_w = \sqrt{F^2 + F_g^2}$ $F_w = \sqrt{80^2 + 196^2} = 212\ \textbf{\textit{N}}\ (= 210\ \underline{N})$	1 1	Allow ecf of incorrect weight from part (i). Need to see unit but only one unit penalty in part (a).
2	**(a)**	**(iii)**	EITHER: Resolving horizontally: $F_W \sin \alpha = 80$ $\sin \alpha = 80/212 = 0.377$ $\alpha = 22(.2)°$ OR: Resolving vertically: $F_W \cos \alpha = 196$ $= 196/212 = 0.925$ $\alpha = 22(.3)°$ OR $\tan \alpha = 80/196$ $\tan \alpha = 0.408$ $\alpha = 22(.2)°$	1 1 1 (1) (1) (1) (1) (1) (1)	Allow ecf of incorrect forces from part i) and ii). Use of $F_W = 210$ N gives $\alpha = 21°$ and use of $F_g = 200$ N as well gives $\alpha = 17°$. All acceptable if working shown.
2	**(b)**	**(i)**	$s = v\,t = 5 \times 4 = 20$ (m)	1	Ignore unit. Accept answer to answer to 1 sf.
2	**(b)**	**(ii)**	$a = dv/dt = (v - u)/t = (9 - 5)/2 = 4/2 = 2\ \underline{m\ s^{-2}}$	1	Unit is required. Accept answer given to 1 sf.
2	**(b)**	**(iii)**	$a = dv/dt = (v - u)/t = \pm (9 - 0)/3$ $a = \pm 3\ \underline{m\ s^{-2}}$	1 1	Appropriate substitution into equation. Unit required but only one unit penalty in (b).
			QUESTION TOTAL	**10**	

Question			Solution	Marks	Guidance
3	(a)	(i)	Total Voltage drop is the sum of voltage drops across all resistors $V_0 = 5 + 2 + 10 = 17$ V	1	Ignore unit.
3	(a)	(ii)	Use of $R = V/I = 17/2$ $R_T = 8.5 \ \underline{\Omega}$	1 1	Substitution of any voltage and 2A into equation. Allow ecf from (i). Unit required
3	(a)	(iii)	$R_1 = 5/2 = 2.5 \ \underline{\Omega}$ $R_2 = 2/2 = 1 \ \underline{\Omega}$ $R_3 = 10/2 = 5 \ \underline{\Omega}$	1 1 1	Units required at least once in part (ii) and part (iii). If already penalised unit in part ii ignore unit. Max 2/3 if not clear which R is which. These marks can be awarded from working shown in part (ii). This is acceptable for both sections.
3	(a)	(iv)	Use of $P = IV$ or $P = I^2R$ or $P = V^2/R$ $P_1 = 2 \times 5 = 10 \ \underline{W}$ $P_1 = (2)^2 \times 2.5 = 10 \ \underline{W}$ $P_1 = 5^2/2.5 = 10 \ \underline{W}$	1 1	Substituting appropriate values into one of the power equations. Unit required.
3	(b)	(i)	Henry (or H)	1	Not h.
3	(b)	(ii)	kg m^2 s^{-2} A^{-2}	1	Third answer should be ringed. Accept alternative clear indication of correct response.
			QUESTION TOTAL	**10**	

Question			Solution	Marks	Guidance
4	**(a)**		<table><tr><td>Ultimate Tensile Stress (UTS)</td><td>4</td></tr><tr><td>Yield Stress</td><td>2</td></tr><tr><td>Fracture Point</td><td>5</td></tr><tr><td>Elastic deformation</td><td>1</td></tr></table>	1 1 1 1	One mark for each correct line of the table.
4	**(b)**	**(i)**	Use of $\sigma = F/A$ hence $A = F/\sigma = 85 \times 10^3 / 105 \times 10^6$ $A = 8.1 \times 10^{-4} \underline{m^2}$ (0.00081 $\underline{m^2}$)	1 1	Allow values (ignoring POT) substituted into $\sigma = F/A$ for first mark. Lose second mark for POT errors. Unit necessary.
4	**(b)**	**(ii)**	$F_y = \sigma_y A = (210 \times 10^6) \times (8.1 \times 10^{-4})$ $F = 1.7 \times 10^5 \underline{N}$ (170 $\underline{kN}$)	1 1	Correct substitution (ignoring POT). Allow ecf from part i) Lose one mark for POT errors Use of $\sigma_y = 105$ MPa scores zero.
4	**(b)**	**(iii)**	$E = \sigma/\varepsilon = 105 \times 10^6 / 500 \times 10^{-6}$ $E = 2.1 \times 10^{11} \underline{Pa}$ (210 $\underline{GPa}$ or 210 000 $\underline{MPa}$)	1 1	Correct substitution (ignoring POT). Lose one mark for POT errors. Unit required.
			QUESTION TOTAL	**10**	

Question			Solution	Marks	Guidance
5	**(a)**		Viscosity is a fluid's ability to resist <u>shear</u> forces.	1	Ignore 'flow'.
5	**(b)**		Laminar flow: <u>particles</u> move in layers/parallel (to direction of flow).	1	IGNORE 'smooth'
			Turbulent flow: <u>particle</u> movement is irregular/chaotic/unpredictable.	1	ACCEPT 'random' Reference to particles needed at least once for both marks. Two opposite statements – max one mark awarded.
5	**(c)**	**(i)**	$P_w = \rho_w \, g \, h_{w\,=}$ 1000 x 9.8 x h	1	Substitution of correct values of ρ_w and g and a value of height for first mark.
			P_w = 1000 x 9.8 x 1 = 9800 <u>Pa</u> or 9.8 <u>kPa</u>	1	Unit required. Lose one mark for POT errors.
5	**(c)**	**(ii)**	$P_m = \rho_m \, g \, h_m$ = 13500 x 9.8 x 0.5	1	Correct substitution required.
			P_m = 6.6 x 10^4 <u>Pa</u> (or 66 <u>kPa</u>)	1	Unit required but penalise only once in part (c). Lose one mark for POT errors, but allow same POT error ecf from part (i).
5	**(c)**	**(iii)**	P_g = 120 + 9.8 + 66 = 196 (kPa)	1	Accept 200 kPa (to 2 sf). Unit not required but consistent values must be added together. Allow ecf from part (i) and (ii).
5	**(c)**	**(iv)**	$P_g = P_{abs} - P_{atm}$	1	First mark for quoting equation or correct substitution.
			P_g = 196 – 100 = 96 (kPa)	1	Unit not required but consistent values must be subtracted. Allow ecf from part (iii).
			QUESTION TOTAL	**10**	

Question			Solution	Marks	Guidance
6		**(i)**	Volume of box = 3 x 3 x 10 = 90 m^3; Conversion of 12 °C to 285 K; Use of $PV = mRT$; $m = PV/RT$; $m = (100 \times 10^3) \times 90/(287 \times 285)$ [= 110 kg]	1 1 1 1	Calculation of volume. Conversion of temperature to K. If T remains in °C max 2 marks can be awarded. Correct rearrangement of equation must be shown, but can be after values have been substituted. Correct substitution and calculation No mark for final value as this is a 'show that' question.
		(ii)	EITHER: Use of $P_1/T_1 = P_2/T_2$ rearranged to give $P_2 = P_1 T_2/T_1$; $P_2 = (100 \times 10^3) \times 300/285 = 1.05 \times 10^5$ <u>Pa</u> (or 105 <u>kPa</u>) OR: Rearrange $PV = mRT$ to give $P = mRT/V$; $P = (110 \times 287 \times 300)/90 = 1.05 \times 10^5$ <u>Pa</u> (or 105 <u>kPa</u>)	1 1 (1) (1)	ACCEPT 1.1 x 10^5 Pa (to 2 sf) Do not accept ecf of other values for m. Unit required. Lose one mark for POT errors. Use of temperatures in °C can score max 1 mark for correct rearrangement. [P = 2500 Pa]
		(iii)	$\Delta T = 300 - 285 = 15$ K; Energy = $m \, c_v \, \Delta T = 110 \times 718 \times 15 = 1.2 \times 10^6$ J	1 1	Correct change in temperature Correct substitution and calculation. Ignore unit Only allow ecf of an incorrect temperature <u>change</u>. [if $T_1 = 12$, then $\Delta T = 288$ and $E = 2.3 \times 10^7$ J; award 1 mark]
		(iv)	Power = energy/time; time = $1.2 \times 10^6/1500$; Time = 800 s (= 13 minutes = 0.22 hours)	1 1	Substitution of values into equation. Allow ecf of energy from part iii). Unit required. Accept 8 x 10^2 s (1sf).
			QUESTION TOTAL	**10**	
			PAPER TOTAL	**60**	

OCR (Oxford Cambridge and RSA Examinations)
1 Hills Road
Cambridge
CB1 2EU

OCR Customer Contact Centre

Education and Learning
Telephone: 01223 553998
Facsimile: 01223 552627
Email: general.qualifications@ocr.org.uk

www.ocr.org.uk

For staff training purposes and as part of our quality assurance
programme your call may be recorded or monitored

PART OF THE
CAMBRIDGE ASSESSMENT
GROUP

UKAS
MANAGEMENT
SYSTEMS
001